SETTING UP GATEWAY (BLEGW-99)



**When setting up lock with gateway, make sure that the BLEGW-99 is plugged in to a power source, within range of the lock and within wi-fi signal range.



 On the admin phone where the lock is registered, go to LOCKS on K3 app

		Locks		+	
	M4			t,	
	pl7				
	RS21			ß	
	t	(]) Info	E Logs	© Sync	
WAREHOUSE new					
Locks		a (र्ट्र Settings	

 Swipe left on the name of the lock you are trying to pair with the gateway and tap INFO

K F	RS2100		
Time Zone	Los Angeles (-07:00)		
Pairing Time 2018-07-17 11:47			
Parameters			
Auto Unlock	Disabled 3		
Gateway Management			
D	elete Lock		
Locks Clier	음 😥 🤃		

3. Scroll down and tap GATEWAY MANAGEMENT

< Gateway Manageme	ent
Setup New Gateway	>
	-
Locks Clients Notifications Se	ttings
Locks Clients Notifications Se	ttings:

4. Tap SET UP NEW GATEWAY

< Gateway Setting				
Name				
Please set a gateway name				
SSID				
Please enter the name of the W-Fi				
Password				
Sync to Lock				
🔒 🖀 🖄 🏟				

5. Set a name for your gateway, fill in the SSID and password for your wi-fi accordingly and tap SYNC TO LOCK



 Follow the instructions that pop up on your phone. (There is a tool inside the BLEGW-99 packaging that can be used to press the setup button).





7. Wait for the gateway to finish pairing with the lock.

< RS	2100			
Gateway Management				
Diagnose Gateway				
Wi-Fi SSID	CRWIFI			
Gateway Name	crp >			
Gateway Model	K3 Gateway 07			
electric imp	Powered by Electric Imp			
Gateway Firmwar	re 00030604			
Gateway Code	01000803			
Gateway ID	30000c2a690c9167			
Gateway Added	2018-07-17 13:57:00			
Locks	Notifications Settings			

Once the gateway is set up, you will see all the information, under the lock it was paired with.