




MOLEX QUICK CONNECT PLUG

MICRO-FIT 3.0™ INTERCONNECT SYSTEM AVAILABLE TO RETROFIT COMMON QUICK CONNECTION SYSTEMS SUCH AS ELECTROLYNX® OR ALLEGION CONNECT®.

Molex 3.0 Key	4-Pin	8-Pin
Female		
Male		



TYPE	WIRE COLOR CODING	STRUCTURE	WIRING CONFIGURATION																																			
8-wire	<p>BACK OF CONNECTOR</p>	<p>Note: 12" length of wire on both end</p>	<table border="1"> <tr><td rowspan="8">8-wire Connector</td><td>1</td><td>Violet</td><td>LBM Normally Closed (N/C)</td></tr> <tr><td>2</td><td>Yellow</td><td>REX Normally Closed (N/C)</td></tr> <tr><td>3</td><td>Orange</td><td>LBM Normally Open (N/O)</td></tr> <tr><td>4</td><td>Blue</td><td>REX Normally Open (N/O)</td></tr> <tr><td>5</td><td>White</td><td>LBM Common (C)</td></tr> <tr><td>6</td><td>Green</td><td>REX Common (C)</td></tr> <tr><td>7</td><td>Black</td><td>Power, negative (-)</td></tr> <tr><td>8</td><td>Red</td><td>Power, positive (-)</td></tr> </table>	8-wire Connector	1	Violet	LBM Normally Closed (N/C)	2	Yellow	REX Normally Closed (N/C)	3	Orange	LBM Normally Open (N/O)	4	Blue	REX Normally Open (N/O)	5	White	LBM Common (C)	6	Green	REX Common (C)	7	Black	Power, negative (-)	8	Red	Power, positive (-)										
8-wire Connector	1	Violet	LBM Normally Closed (N/C)																																			
	2	Yellow	REX Normally Closed (N/C)																																			
	3	Orange	LBM Normally Open (N/O)																																			
	4	Blue	REX Normally Open (N/O)																																			
	5	White	LBM Common (C)																																			
	6	Green	REX Common (C)																																			
	7	Black	Power, negative (-)																																			
	8	Red	Power, positive (-)																																			
12-wire	<p>BACK OF CONNECTOR</p>	<p>Note: 12" Length of wire on both end</p>	<table border="1"> <tr><td rowspan="8">8-wire Connector</td><td>1</td><td>Brown</td><td>LBM Normally Closed (N/C)</td></tr> <tr><td>2</td><td>Yellow</td><td>REX Normally Closed (N/C)</td></tr> <tr><td>3</td><td>Orange</td><td>LBM Normally Open (N/O)</td></tr> <tr><td>4</td><td>Blue</td><td>REX Normally Open (N/O)</td></tr> <tr><td>5</td><td>White</td><td>LBM Common (C)</td></tr> <tr><td>6</td><td>Green</td><td>REX Common (C)</td></tr> <tr><td>7</td><td>Black</td><td>Power, negative (-)</td></tr> <tr><td>8</td><td>Red</td><td>Power, positive (-)</td></tr> </table> <table border="1"> <tr><td rowspan="4">4-wire Connector</td><td>1</td><td>Pink</td><td rowspan="4">As assigned</td></tr> <tr><td>2</td><td>Tan</td></tr> <tr><td>3</td><td>Violet</td></tr> <tr><td>4</td><td>Grey</td></tr> </table>	8-wire Connector	1	Brown	LBM Normally Closed (N/C)	2	Yellow	REX Normally Closed (N/C)	3	Orange	LBM Normally Open (N/O)	4	Blue	REX Normally Open (N/O)	5	White	LBM Common (C)	6	Green	REX Common (C)	7	Black	Power, negative (-)	8	Red	Power, positive (-)	4-wire Connector	1	Pink	As assigned	2	Tan	3	Violet	4	Grey
8-wire Connector	1	Brown	LBM Normally Closed (N/C)																																			
	2	Yellow	REX Normally Closed (N/C)																																			
	3	Orange	LBM Normally Open (N/O)																																			
	4	Blue	REX Normally Open (N/O)																																			
	5	White	LBM Common (C)																																			
	6	Green	REX Common (C)																																			
	7	Black	Power, negative (-)																																			
	8	Red	Power, positive (-)																																			
4-wire Connector	1	Pink	As assigned																																			
	2	Tan																																				
	3	Violet																																				
	4	Grey																																				